



Motori asincroni monofase autofrenanti serie AM - AE - AA - AP - CM - CP
AM - AE - AA - AP - CM - CP series single-phase induction brake motors
Moteurs asynchrones monophasés autofreinants série AM - AE - AA - AP - CM - CP
Asynchrone Wechselstrombremsmotoren Serie AM - AE - AA - AP - CM - CP

6 POLI 1000 rpm - Volt 230/50 Hz

TIPO TYPE	Autofrenante in D.C. Brake motor in D.C.				Autofrenante serie S in D.C. S series safety brake in D.C.				Autofrenante positivo in D.C. Positive brake in D.C.			
	CF	Cicli/h Cycles/h	PB	Peso Weight	CF	Cicli/h Cycles/h	PB	Peso Weight	CF	Cicli/h Cycles/h	PB	Peso Weight
	Nm	∅	Watt	Kg	Nm	∅	Watt	Kg	Nm	∅	Watt	Kg
AM56B	1	21500	12	5,0	-	-	-	-	-	-	-	-
AM63B	4	18000	20	6,0	3	18000	17	6,0	8,0	18000	11,5	4,65
AM63C	4	18000	20	6,0	3	18000	17	6,0	8,0	18000	11,5	4,95
AM71B	4	25000	20	9,0	4	25000	17	8,0	8,0	25000	11,5	7,05
AM71C	4	24000	20	9,0	4	24000	17	9,0	8,0	24000	11,5	7,95
AM80B	8	16000	25	11,0	9	16000	34	12,0	15,0	16000	16,0	9,80
AM80C	8	15000	25	14,0	9	15000	34	13,0	15,0	15000	16,0	11,60
AM90L	16	13500	30	19,0	10	13500	34	17,0	30,0	13500	16,0	14,60
AM90LB	16	13000	30	24,0	10	13000	34	19,0	30,0	13000	16,0	16,60
AM100B	32	7000	40	28,5	12	7000	40	26,5	60,0	7000	21,0	22,90
AM100BL	32	7000	40	30,5	12	7000	40	28,5	60,0	7000	21,0	24,90